

Mobile Recharge System APIs

Bonrix Software System - Mobile Recharge System API List:

=====
For Recharge:
=====

<http://localhost:8090/APIs.aspx?Mob=9429045500&message=Rr+vodafone+9426045500+20+1234&mytxid=404>

Rr = RechargeType
Vodafone or(Vf) = Service name or Service Short Name
9426045500 = CustomerMobileNo
20 = RechargeAmount
1234 = Pin & 404=clients transaction id. Here '&mytxid=404' is optional

Reply : Request Status :Success.,Time:44(s),TxId:61,Bal:1940,Vodafone*20*9978540353

=====
For STV(Special Tariffs Voucher)
=====

<http://localhost:8090/APIs.aspx?Mob=9429045500&message=STV+vf+9426045500+20+1234&mytxid=404>

STV = RechargeType
Vodafone or(Vf) = Service name or Service Short Name
9426045500 = CustomerMobileNo
20 = RechargeAmount
1234 = Pin & 404=clients transaction id. Here '&mytxid=404' is optional

Reply : Request Status :Success.,Time:44(s),TxId:61,Bal:1940,Vodafone*20*9978540353

=====
For Balance:
=====

To know the balance

<http://localhost:8090/APIs.aspx?Mob=9429045500&message=Bal+1234>

Bal = Command for balance
1234 = Pin

Reply : Your Balance is 1960

=====
For Last transaction:
=====

To know about last transaction.

<http://localhost:8090/APIs.aspx?Mob=9429045500&message=Last+1234>

Last = Command for last transaction.
1234 = Pin

Reply : Status :Timeout, 9426045500*Vodafone*20

=====
For Details of perticular transction based on system's Transaction Id:
=====

<http://localhost:8090/APIs.aspx?Mob=9429045500&message=TxId+10+1234>

TxId = transaction id command
1234 = pin
10 = Transaction id

Reply : Status :Timeout, 9426045500*Vodafone*2

=====
For Details of perticular transction based on client's Transaction id:
=====

<http://localhost:8090/SmsRechargeRequest?Mob=9429045500&message=myTxId+12+1234>

myTxId = Client System Transaction Id
1234 = pin
10 = Transaction id

Reply: Status :Timeout, 9426045500*Vodafone*20

=====
For authentication of member
=====

<http://localhost:1129/ReCharge/APIs.aspx?Mob=9428045500&message=Auth+6226>

9428099500 = MobileNo
Auth=command
6226 = Pin

Reply: true Dealer

=====
Payment Transfer:
=====

<http://localhost:1129/Recharge/APIs.aspx?Mob=9925645235&message=TFR+9425556120+50+1234>

TRF = Command for payment transfer.
9425556120=mobile no of person to transfer money.
50=Payment Amount.
1234 = Pin.

Reply: Your 50 Rs Payment Transfer is Successful. Your new balance is 1950.
New balance of 9425556120 is 1050.

=====
For Revert Balance
=====

<http://localhost:1129/Recharge/APIs.aspx?Mob=87989456370&message=RET+9433044440+5+1234>

RET = Command for Revert Balance.
9433044440=mobile no of person to Revert money.
5=Revert Amount.
1234 = Pin.

Reply: Your 50 Rs Payment Revert is Successful. Your new balance is 2050. New balance of 87989456370 is 950.

=====
For Complaint Request
=====

<http://localhost:1129/Recharge/APIs.aspx?Mob=87989456370&message=com+12+1234+Remark>

com = Command for Complaint Request.
12=Rechargeid.
1234 = Pin.
Remark=complaint Remark .It is Optional

Reply: We have registered your complaint. Your ComplaintId is 12

=====
For Complaint Status
=====

<http://localhost:1129/Recharge/APIs.aspx?Mob=87989456370&message=comstatus+12+1234>

comstatus = Command for Complaint Status.
12=Complain Id.
1234 = Pin.

Reply: Pending